



WiFi/SMS/GSM Alarm System

Triple protection for your home

EM8615

EAN: 8716065326789

Packaging contents: 1 x Alarm system with built-in WiFi & mobile module, siren and 1 back-up battery. (EM8615), 1 x wireless door/window contact. (EM8660), 1 x wireless PIR motion detector. (EM8650), 2 x multifunctional remote controls. (EM8621), 1 x power adapter for the Alarm system, 2 x window alarm stickers, All required batteries, QIG

OVERVIEW

- Complete ready-to-go wireless alarm system
- No subscription and no fixed monthly costs required
- Install and control the WiFi / SMS / GSM alarm system with the free Android or iOS app
- Sends a push notification (via the internet), SMS message and calls during an alarm
- Easy to install anywhere thanks to the SMS / GSM function

COMPATIBLE OPERATING SYSTEM

- Required operating system for the use of the EM8615 app: Android, IOS. (other cell phones are supported via text messages)

SPECIFICATIONS

Alarm System

- Mobile GSM frequency: 850 / 900 / 1800 / 1900MHz
- Communication protocols: Communicates via LAN IP(WiFi) and/or GSM
- Wi-Fi support: 802.11b/g/n
- Power supply input: 110 – 240V AC 50-60Hz
- Power supply output: 12V DC 800mA
- Stand-by current: 60mA
- Alarm current: 120mA
- Power consumption: 1,6W
- Back-up battery: Lithium-Ion battery 7,4V 500mA
- Internal siren: 90dB
- Maximum amount of sensors:
 - 10 x Remote controls
 - 100 x Wireless sensors
- Sensor frequency: 433MHz
- Temperature: -10 to 55 degrees Celsius
- Humidity: < 80% (no condensing)
- Dimensions in mm. (WxHxD): 50 x 150 x 160
- Weight in grams: 354

Motion Detector

- Motion detector (WxHxD) in mm: 108 x 52 x 37
- Bracket in mm. (WxHxD) bracket: 52 x 30 x 26,5
- Weight in grams: 114
- Power supply: 3V DC (2 x AA 1,5V LR6)
- Stand-by current: <30uA
- Alarm current: <15mA
- Detection reach: 8 meters / 110 degrees
- Wireless reach: Max. 80 meters (open field)
- Frequency sensors: 433MHz
- Temperature: -10 to 55 degrees Celsius
- Humidity: < 80% (no condensing)
- The motion detector will not be triggered by pets less than 25kg and movements of pets below the 45cm measured from the ground. Please note that jumping pets can trigger the alarm

Door/Window Contact

- Sensor (WxHxD) in mm: 70 x 34 x 17,5
- Magnet (WxHxD) in mm: magnet: 51 x 12 x 13,5
- Weight in grams: 54
- Power supply: 1,5V DC (2 x AA 1,5V LR6)
- Stand-by current: <30uA
- Alarm current: <40mA
- Wireless reach: Max. 80 meters (open field)
- Frequency sensors: 433MHz
- Temperature: -10 to 55 degrees Celsius
- Humidity: < 80% (no condensing)

Remote

- Dimensions in mm. (WxHxD): 31 x 57 x 11
- Weight in grams: 14
- Power supply: 3V DC (1 x CR2025 button battery)
- Stand-by current: <10uA
- Operation current: <7mA
- Frequency remote: 433MHz
- Temperature: -10 to 55 degrees Celsius
- Humidity: < 80% (no condensing)

WiFi/SMS/GSM Alarm System

Triple protection for your home

DESCRIPTION

Are you looking for a reliable alarm system which can be installed with a free app without having any subscriptions or monthly fees? The EM8615 WiFi/SMS/GSM Alarm System provides a solid foundation for securing your home. Connect the alarm system to your network wirelessly and receive push notifications on your smartphone. You can use a GSM sim card as well and receive a phone call or SMS text message during an alarm. Very convenient when you do not have Internet on your smartphone. The EM8615 set includes a base station with internal siren, 1 motion detector, 1 door/window contact, 2 remote controls and 2 window stickers. Because of the wireless communication the EM8615 starter kit can be extended with additional sensors. The alarm system remains working during a power failure thanks to the built-in backup battery.

Complete starter kit

The EM8615 WiFi/SMS/GSM Alarm System Starter Kit enables you to build your own safe environment. The kit includes a base station with built-in siren and back-up battery, 1 motion detector, 1 door/window contact, 2 remote controls, 2 window stickers and a quick install guide.

Wireless connection to your network and easy installing a GSM sim card

Connect the EM8615 easily to your wireless network. You will receive an Internet push notification on your smartphone during an alarm. For even a better security you can install a GSM sim card in the alarm system. The EM8615 will send a SMS text message or will call in case of an emergency. Convenient when your phone is not connected to the Internet. Thanks to the GSM function it is possible to call to the alarm system and listen along in your home.

Triple protection for your personal belongings: also during a power failure

Receive directly a notification on you smartphone during an alarm: a push notification, SMS text message or phone call. The free Android and iOS app enables you to set-up 5 phone numbers which need to receive alarm notifications. The alarm system remains working during a power failure thanks to the backup battery. During a power failure the alarm system will fall back to the SMS/GSM function to guarantee the safety of your personal belongings.

Easy to install everywhere

The EM8615 base station needs a fixed power point. All accessories are battery powered and are completely wireless. Nevertheless, the alarm system can be located easily everywhere. Thanks to the GSM functionality the EM8615 is also usable on locations without an Internet connection.

Works without a subscription or fixed monthly fees

The alarm system works via WiFi or with a GSM sim card. There are no monthly fees or subscriptions required.

Full configurable and controllable with the free iOS/Android app or via SMS text messages

Use the free EM8615 iOS or Android app to configure and control the WiFi/SMS/GSM alarm system. You can use the app via your wireless home network or mobile Internet connection everywhere in the world. No Internet connection available? Don't worry. Use SMS text messages to configure and control the alarm system.

Control the alarm system easily via the enclosed remote control

Control the EM8615 Alarm System with the enclosed remote control. You can attach the remote control easily to your keychain. The remote control allows you to arm and disarm the alarm system and activate the home mode or SOS function.

Extendable up to 100 sensors

You are ready for the future with the EM8615. Extend the alarm system with a maximum of 100 sensors, such as motion detectors, door/window contacts, smoke detectors, sirens and remote controls. It is possible to create up to 9 sensors with their own unique name to know directly which sensor warns you. Convenient right!

Four pre-programmed alarm groups

The alarm system has 4 different alarm groups in which you can locate the sensors. Each group has its own characteristics to protect your home to the max.

WiFi/SMS/GSM Alarm System

Triple protection for your home

IMAGES

